

APPENDIX A

Complete Set of Claims Showing Amendments

1. [AMENDED] A method of [adaptively] controlling [system] stability of an on-frequency repeater, the method comprising steps of:

generating a signature signal [uniquely] associated with the repeater;

inserting the signature signal into a first RF signal transmitted by the repeater;

detecting a correlation between the signature signal and a second RF signal received by the repeater;

and

controlling an effective radiated power (ERP) of the first RF signal transmitted by the repeater, based on the detected correlation.
2. [AMENDED] A method as claimed in claim 1, wherein the step of generating the signature signal comprises steps of:

generating a [unique] code signal; and

shaping the code signal.
3. [AMENDED] A method as claimed in claim 2, wherein the step of generating [a unique] the code signal comprises a step of generating a [unique] predetermined sequence of bits.
4. [AMENDED] A method as claimed in claim 3, wherein the predetermined sequence of bits is spectrally white.

APPENDIX A

5. [AMENDED] A method as claimed in claim 3, wherein the predetermined sequence of bits is pre-selected from among a set of orthogonal bit sequences.
6. A method as claimed in claim 2, wherein the step of shaping the code signal comprises a step of modulating the code signal with a predetermined fade signal.
7. [AMENDED] A method as claimed in claim 1, wherein the step of inserting the signature signal into [a] the first RF signal comprises a step of modulating a parameter of the first RF signal.
8. A method as claimed in claim 7, wherein the parameter comprises one or more of: a power level and a phase.
9. A method as claimed in claim 7, wherein the step of modulating the parameter of the first RF signal comprises simultaneously modulating the parameter of all RF signals within a predetermined wide-band signal path.
10. [AMENDED] A method as claimed in claim 1, wherein the step of detecting a correlation between the signature signal and [a] the second RF signal comprises steps of:

monitoring the second RF signal to detect at least a
 signal component consistent with the signature
 signal;

comparing the detected signal component to the
 signature signal, and generating a correlation

APPENDIX A

signal indicative of a degree of similarity between the detected signal component and the signature signal.

11. A method as claimed in claim 10, wherein the step of monitoring the second RF signal comprises steps of:
sampling the second RF signal;
digitally filtering the sample signal;
comparing the filtered signal to a predetermined threshold; and
generating the signal component based on the comparison result.
12. A method as claimed in claim 10, wherein the step of comparing the detected signal component to the signature signal comprises steps of:
logically comparing respective successive bits of each of the detected signal component and the signature signal; and
averaging the comparison result.
13. A method as claimed in claim 12, wherein the step of logically comparing respective successive bits comprises either one of Exclusive ORing, and ANDing successive bits of each of the detected signal component and the signature signal.
14. A method as claimed in claim 10, wherein the step of comparing the detected signal component to the signature signal comprises steps of:

APPENDIX A

calculating a cross-correlation of the detected signal component and the signature signal; and
comparing the calculation result to a predetermined threshold.

15. [AMENDED] A method as claimed in claim 1, wherein the step of controlling an effective radiated power (ERP) of the first RF signal comprises steps [f] of:
comparing the detected correlation to a predetermined threshold value; and
determining an optimum value of a gain of the repeater using the comparison result.

16. [AMENDED] A system for [adaptively] controlling a [system] stability of an on-frequency repeater of a wireless communications network, the system comprising:
a signal generator adapted to generate a signature signal [uniquely] associated with the repeater;
a first modulator adapted to insert the signature signal into a first RF signal transmitted by the repeater;
a detector adapted to detect a correlation between the signature signal and a second RF signal received by the repeater; and
a [micro-]controller adapted to control an effective radiated power (ERP) of the first RF signal transmitted by the repeater, based on the detected correlation.

APPENDIX A

17. [AMENDED] A system as claimed in claim 16, wherein the signal generator comprises:

a code generator adapted to generate a [unique] code signal; and

a signal [processor] shaper adapted to shape the code signal.
18. [AMENDED] A system as claimed in claim 17, wherein the code signal comprises a [unique] predetermined sequence of bits.
19. [AMENDED] A system as claimed in claim 18, wherein the predetermined sequence of bits is spectrally white.
20. [AMENDED] A system as claimed in claim 18, wherein the predetermined sequence of bits is pre-selected from among a set of orthogonal bit sequences.
21. [AMENDED] A system as claimed in claim 17, wherein the signal [processor] shaper comprises a second modulator adapted to modulate the code signal with a predetermined fade signal.
22. A system as claimed in claim 16, wherein the first modulator is adapted to modulate a parameter of the first RF signal.
23. A system as claimed in claim 22, wherein the parameter comprises one or more of: a power level and a phase.

APPENDIX A

24. [AMENDED] A system as claimed in claim 22, wherein the first modulator is adapted to simultaneously modulate the parameter of all RF signals within a predetermined wide-band signal path.
25. A system as claimed in claim 16, wherein the detector comprises:
 - a monitor adapted to detect at least a signal component of the second RF signal that is consistent with the signature signal; and
 - a first comparator adapted to compare the detected signal component to the signature signal, and generate a correlation signal indicative of a degree of similarity between the detected signal component and the signature signal.
26. A system as claimed in claim 25, wherein the monitor comprises:
 - a sampler for sampling the second RF signal;
 - a filter adapted to digitally filter the sample signal;
 - a second comparator for comparing the filtered signal to a predetermined threshold, and generate the signal component based on the comparison result.
27. A system as claimed in claim 26, wherein the first comparator comprises:
 - a first signal processor adapted to logically compare respective successive bits of each of the

APPENDIX A

detected signal component and the signature signal; and

a second signal processor adapted to average the comparison result.

28. A system as claimed in claim 27, wherein the first signal processor comprises either one of an Exclusive OR logic gate, and an AND logic gate.

29. [AMENDED] A system as claimed in claim 26, wherein the first comparator comprises a third signal processor adapted to calculate a cross-correlation of the detected signal component and the signature signal.

30. [AMENDED] A system as claimed in claim 16, wherein the [micro-]controller is adapted to operate under control of software code to:

compare the detected correlation to a predetermined threshold value; and

[determining] determine an optimum value of a gain of the repeater using the comparison result.

31. [AMENDED] A method of controlling spatial nulls within an area of overlapping coverage served by at least two transmitters, the method comprising a step of:

generating a signature signal [uniquely] associated with a selected [transmitter] one of the transmitters, the signature signal being unique

APPENDIX A

among at least the transmitters serving the area
of overlapping coverage; and

modulating a respective RF signal transmitted by the
selected transmitter, using the signature signal;
whereby modulation of the RF signal causes a
corresponding movement of spatial nulls within
the area of overlapping coverage.

32. [AMENDED] A method as claimed in claim 31, wherein
the step of generating the signature signal comprises
a step of generating a [unique] code signal.
33. [AMENDED] A method as claimed in claim 32, wherein
the [unique] code signal comprises a [unique]
sequence of bits.
34. A method as claimed in claim 33, wherein the sequence
of bits is spectrally white.
35. A method as claimed in claim 33, wherein the sequence
of bits is pre-selected from among a set of
predetermined orthogonal bit sequences.
36. A method as claimed in claim 31, wherein the step of
modulating a respective RF signal transmitted by the
selected transmitter comprises a step of controlling
a parameter of the RF signal in accordance with the
signature signal.
37. A method as claimed in claim 36, wherein the
parameter comprises either one or both of a power
level and a signal phase.

APPENDIX A

38. [AMENDED] A method as claimed in claim 36, wherein the [a] step of controlling the parameter comprises a step of simultaneously controlling the parameter of all RF [signals] signal traffic within a predetermined wide-band signal path of the selected transmitter.
39. [AMENDED] A system for controlling spatial nulls within an area of overlapping coverage served by at least two transmitters, the [method] system comprising [a step of]:
- a signal generator adapted to generate a signature signal [uniquely] associated with a selected [transmitter] one of the transmitters, the signature signal being unique among at least the transmitters serving the area of overlapping coverage; and
- a modulator adapted to modulate a respective RF signal transmitted by the selected transmitter, using the signature signal;
- whereby modulation of the RF signal causes a corresponding movement of spatial nulls within the area of overlapping coverage.
40. [AMENDED] A system as claimed in claim 39, wherein the signature signal is derived from a [unique] code signal.
41. [AMENDED] A system as claimed in claim 40, wherein the [unique] code signal comprises a [unique] sequence of bits.

APPENDIX A

42. A system as claimed in claim 41, wherein the sequence of bits is spectrally white.
43. A system as claimed in claim 41, wherein the sequence of bits is pre-selected from among a set of predetermined orthogonal bit sequences.
44. A system as claimed in claim 39, wherein the modulator is adapted to control a parameter of the RF signal in accordance with the signature signal.
45. A system as claimed in claim 44, wherein the parameter comprises either one or both of a power level and a signal phase.
46. [AMENDED] A system as claimed in claim 44, wherein the modulator is adapted to simultaneously control the parameter of all RF [signals] signal traffic within a predetermined wide-band signal path of the selected transmitter.
47. [NEW] A repeater adapted to control spatial nulls within an area of overlapping coverage served by the repeater and at least one other transmitter, the repeater comprising:

a signal generator adapted to generate a signature signal associated with the repeater, the signature signal being unique among the repeater and each other transmitter serving the area of overlapping coverage; and

APPENDIX A

a modulator adapted to modulate a respective signal transmitted by the repeater, using the signature signal;

whereby modulation of the signal causes a corresponding movement of spatial nulls within the area of overlapping coverage.

48. [NEW] A repeater as claimed in claim 47, wherein the signature signal is derived from a code signal.
49. [NEW] A repeater as claimed in claim 48, wherein the code signal comprises a sequence of bits.
50. [NEW] A repeater as claimed in claim 49, wherein the sequence of bits is spectrally white.
51. [NEW] A repeater as claimed in claim 49, wherein the sequence of bits is pre-selected from among a set of predetermined orthogonal bit sequences.
52. [NEW] A repeater as claimed in claim 48, wherein the modulator is adapted to control a parameter of the signal in accordance with the signature signal.
53. [NEW] A repeater as claimed in claim 52, wherein the parameter comprises either one or both of a power level and a signal phase.
54. [NEW] A repeater as claimed in claim 52, wherein the modulator is adapted to simultaneously control the parameter of all signal traffic within a

APPENDIX A

predetermined wide-band signal path of the selected transmitter.

55. [NEW] A method as claimed in claim 1, wherein the signature signal associated with the repeater differs from the respective signature signal associated with at least one other repeater.
56. [NEW] A system as claimed in claim 16, wherein the signature signal associated with the repeater differs from the respective signature signal associated with at least one other repeater.
57. [NEW] An on-frequency repeater of a wireless communications network, the repeater comprising:
- a signal generator adapted to generate a signature signal associated with the repeater;
 - a first modulator adapted to insert the signature signal into a first signal transmitted by the repeater;
 - a detector adapted to detect a correlation between the signature signal and a second signal received by the repeater; and
 - a controller adapted to control an effective radiated power (ERP) of the first signal transmitted by the repeater, based on the detected correlation.
58. [NEW] An on-frequency repeater as claimed in claim 57, wherein the signature signal associated with the repeater differs from the respective signature signal associated with another repeater.

APPENDIX A

59. [NEW] An on-frequency repeater as claimed in claim 57, wherein the signal generator comprises:
a code generator adapted to generate a code signal;
and
a signal shaper adapted to shape the code signal.
60. [NEW] An on-frequency repeater as claimed in claim 59, wherein the code signal comprises a predetermined sequence of bits.
61. [NEW] An on-frequency repeater as claimed in claim 60, wherein the predetermined sequence of bits is spectrally white.
62. [NEW] An on-frequency repeater as claimed in claim 60, wherein the predetermined sequence of bits is pre-selected from among a set of orthogonal bit sequences.
63. [NEW] An on-frequency repeater as claimed in claim 59, wherein the signal shaper comprises a second modulator adapted to modulate the code signal with a predetermined fade signal.
64. [NEW] An on-frequency repeater as claimed in claim 57, wherein the first modulator is adapted to modulate a parameter of the first RF signal.
65. [NEW] An on-frequency repeater as claimed in claim 64, wherein the parameter comprises one or more of: a power level and a phase.

APPENDIX A

66. [NEW] An on-frequency repeater as claimed in claim 64, wherein the first modulator is adapted to simultaneously modulate the parameter of all signals within a predetermined wide-band signal path.
67. [NEW] An on-frequency repeater as claimed in claim 57, wherein the detector comprises:
- a monitor adapted to detect at least a signal component of the second signal that is consistent with the signature signal; and
 - a first comparator adapted to compare the detected signal component to the signature signal, and generate a correlation signal indicative of a degree of similarity between the detected signal component and the signature signal.
68. [NEW] An on-frequency repeater as claimed in claim 67, wherein the monitor comprises:
- a sampler for sampling the second signal;
 - a filter adapted to digitally filter the sample signal;
 - a second comparator for comparing the filtered signal to a predetermined threshold, and generate the signal component based on the comparison result.
69. [NEW] An on-frequency repeater as claimed in claim 67, wherein the first comparator comprises:
- a first signal processor adapted to logically compare respective successive bits of each of the

APPENDIX A

detected signal component and the signature
signal; and

a second signal processor adapted to average the
comparison result.

70. [NEW] An on-frequency repeater as claimed in
claim 69, wherein the first signal processor
comprises either one of an Exclusive OR logic gate,
and an AND logic gate.

71. [NEW] An on-frequency repeater as claimed in
claim 69, wherein the first comparator comprises a
third signal processor adapted to calculate a
cross-correlation of the detected signal component
and the signature signal.

72. [NEW] An on-frequency repeater as claimed in
claim 57, wherein the controller is adapted to
operate under control of software code to:

compare the detected correlation to a predetermined
threshold value; and

determine an optimum value of a gain of the repeater
using the comparison result.